

Our 1000W and 2000W dimmers in 0-10V slave for 1 control zone are specially designed for dimming CBM brand LED lamps.

- Manual function with its adjustment knob.
- Minimum 1% adjustment with internal potentiometer.
- Dimmable from 0.2% to 100% without flashing/flickering.

(Non contractual photo).



Reference	ECO-5A	ECO-10A
Designation	Dimmer 0-10V	Dimmer 0-10V
Nominal Consumption Zone Number	1100W – 5Amps / 1 zone	2200W – 10Amps / 1 zone
Power load	80% recommended nominal load, i.e., <u>1000W</u>	80% recommended nominal load, i.e., <u>2000W</u>
Entrance	120/208/230/240 VAC	
Maximum quantity in installed tubes	60 tubes of 18W dimmable	110 tubes of 18W dimmable
Dimming	from 0.2% to 100% without flickering (CBM brand luminaire)	
Mode	Slave	
Function	0-10V	
Tension/Frequency	230 VAC - 50/60 Hz	
Dimensions	220mm x 90mm x 180mm	
Water - Shock Protection	IP20 – IK10	
Guarantee	2 years (against any manufacturing defect)	